

# **Transmitter/Controller**

for pH-Value, Redox, Standard signals and Temperature



measuring • monitoring • analysing



KOBOLD companies worldwide:

ARGENTINA, AUSTRALIA, AUSTRIA, BELGIUM, BULGARIA, CANADA, CHILE, CHINA, COLOMBIA, CZECHIA, EGYPT, FRANCE, GERMANY, GREAT BRITAIN, HUNGARY, INDIA, INDONESIA, ITALY, MALAYSIA, MEXICO, NETHERLANDS, PERU, POLAND, REPUBLIC OF KOREA, ROMANIA, SINGAPORE, SPAIN, SWITZERLAND, TAIWAN, THAILAND, TUNISIA, TURKEY, USA, VIETNAM KOBOLD Messring GmbH Nordring 22-24 D-65719 Hofheim/Ts. ♦ Head Office: +49(0)6192 299-0 ♦ +49(0)6192 23398 info.de@kobold.com www.kobold.com

1



# Description

The compact transmitter /controller APM-1.. measures and controls the pH value or redox potential in aqueous solutions. It is available as panel-mounted device according to DIN/EN 61554 or as field housing.

Measured values and parameters are displayed on a high-contrast graphic display in plain text.

Easy configuration via buttons or PC with optional software provide a simple and user friendly operation.

An integrated math and logic module enables the integration of the measured values in mathematical formulas so that the measured variables can be displayed.

The transmitter has two analogue and two binary inputs.

- Analogue input:
  - For pH- or redox sensor

Conventional glass sensors, combined electrode or ISFET sensors can be attached.

- Compensation input: For connection of a resistance thermometer Pt 100/Pt1000/NTC/PTC a standard signal 0(4)...20 mA, 0(2)...10 V) or resistance transmitter (min. 100 Ω, max. 3 kΩ)
- 2 binary inputs

As initiators for actions (keyboard inhibit, Hold, Alarm suppression, reset partial or total quantity, parameter set changeover) or connecting a pulse encoder e. g. for flow measurement (instantaneous value, partial quantity, total quantity)

The two control relays can be used as limit value or two position, three position controller or continuous controller with P-, PI-, PD- or PID action.

The modular units can be retrofitted with 3 plug-in boards and so be upgraded flexibly for different measuring and control tasks

The followings boards are available:

- input standard signal 0(4) ... 20 mA, 0(2) ... 10V
- supply for ISFET sensor 5V
- supply for proximity switch
- analogue output 0(4)...20 mA, 0(2)...10 V
- 1 relay (changeover contact)
- 2 relay (NO with common pin)
- semiconductor relay TRIAC 1A
- semiconductor switch Photo-Mos
- interface RS 485 (max. 1)
- interface Profibus DP (max. 1)
- datalogger (max. 1)

# A complete measuring device comprises:

- the pH transmitter model APM-1
- a pH combined electrode model APS-Z with integrated or separate temperature sensor Pt 100 model AZT-Z
- a suitable pH measuring cable model APK-Z

#### Application examples for pH measurements

## Drinking water

Monitoring parameters

# Industrial waste-water treatment

- Neutralization
- Detoxication
- Precipitation station
- Final inspection

## Communal waste-water treatment plants

- Inflow /sand-trap
- Activation tanks (for nitrification)
- Run-off
- Digestion tower


# **Functional description**

The parameters of the units can be easily configured via keyboard or optional software via PC. The operation is protected by a password. Up to 8 user data that must be changed frequently, can be unblocked in one user file.


## Display


The display is a graphic display in plain text. Different displays can be configurated by customer. Large display, double display, bargarph, trend curve with various status indicators and alarms.

# Normal display














Large display









No responsibility taken for errors; subject to change without prior notice.



# Calibration

For units with additional plug-in boards the following calibration options are possible:

Zero point, limit value, zero point and limit value, cell constant, temperature coefficient.

## Linear scaling

With function "linear scaling" the input signal can be displayed linearly. The following units are available:  $\mu$ S/cm, mS/cm, %, mV, pH, ppm, customised up to 5 characters.

#### **Customised with table**

Nonlinear relationships between input and output size can be processed. E. g. Content of horizontal cylinders in level measurement. The values can be stored in a table via software.

## Calibration

1, 2 or 3-point calibration for pH and 1-point calibration for Redox (for display mV) or 2-point calibration for Redox (%-display, free scaling).

The last 5 successful calibrations can be stored in a logbook.

# Wash timer

Cyclically recurring actions can be triggered by activation of a relay.

#### **Technical Data**

C	Эe	en	e	al

Housing:	Plastic, for panel mounting according to DIN IEC 61554 or aluminum field housing, orange		
Ambient temperature:	-5+55°C (panel mounting) -5+50°C (field housing)		
Storage temperature:	-30+70°C		
Climatic rating:	rel. humidity $\leq 90\%$ annual mean, no condensation		
Mounting position:	horizontal		
Weight: Insta	allation housing: approx. 380 g (fully fitted with 3 optional boards)		
Field	d housing: approx. 1780 g		
Protection:	Installation housing: IP 65 (front), IP 20 (rear) Field housing: IP 65		
Display:	LC graphic display, 122 x 32 Pixel blue with backlight		
Power supply:	110240 V <sub>AC</sub> , -15/+10%, 4863 Hz (standard) 2030 V <sub>AC/DC</sub> , 4863 Hz (special)		
Power consumption :	max. 13 VA		
Data backup:	EEPROM		
Electrican connection:	screw terminals (rear) max. cable cross-section 2.5 mm <sup>2</sup>		
Menu languages:	German (factory set), English, French, Spanish, Dutch, Russian, Hungarian, Italian, Czech, Swedish, Portuguese, Polish, Rumanian		

# Input 1 (standard)

(pH or Redox)

# pH-value

Measuring and control range: Accuracy: Temperature effect: Ambient temperature effect:

-2...16 pH  $\leq$  0.3 % of measuring range 0.2 % /10 K

-10...+150°C (note values of the sensor)

 $0.1 \dots 30 \text{ k}\Omega$  (entry via table

 $\leq$  1.5% of measuring range

with 20 value pairs)

# Redox potential

Measuring and	
control range:	-15001500 mV
Accuracy:	$\leq$ 0.3 % of measuring range
Ambient	
temperature effect:	0.2%/10K

#### Input 2 (standard)

(Temperature, standard signal or resistance)

#### Temperature Pt100/Pt1000

Measuring and	
control range:	-50+250°C (switchable to °F)
Accuracy:	≤0.25% of measuring range
Ambient	
temperature effect:	0.2 % /10 K

#### **Temperature NTC/PTC**

Measuring and control range: Accuracy: Ambient

temperature effect: 0.2 % /10 K

#### Standard signal

Measuring and	
control range:	0(4) 20 mA or 0 10 V
Accuracy:	0.25 % of measuring range
Ambient	
temperature effect:	0.2%/10K

#### **Resistance transmitter**

Measuring and	
control range:	minimal: 100 $\Omega$ , maximal 3 k $\Omega$
Accuracy:	±5Ω
Ambient	
temperature effect:	0.1 % /10 K
Binary inputs (stand	ard)
Activation	Electing contact is open; function

Activation:	Floating contact is open: function is not active Floating contact is closed: function is active
Function:	Key lock, manual mode, HOLD, HOLD inverse, alarm suppression, freeze measured value, level lock, reset partial quantity, reset total quantity, parameter set changeover



Technical	Data	(suite)
-----------	------	---------

	<i>י</i> ן			
Outputs (standard)		Outputs (optional ma	ах. З)	
2 relay (changeover of Contact rating: Contact service life:	<b>contact)</b> 5 A at 240 V <sub>AC</sub> resistive load 350 000 operations at nominal load 750 000 operations at 1 A	<b>Optional board 1 rel</b> Switching function: Contact rating: Contact service life:	ay changeover contact 8 A at 240 V <sub>AC</sub> resistive load 100 000 operations at nominal load 350 000 operations at 3 A	
Sensor supply for 2-	wire transmitter	Optional board double relay		
17 $V_{DC}$ at 20 mA, oper	n-circuit voltage approx. 25 $V_{DC}$	Switching function:	NO with common pin	
Controller (standard) (see manual for config		Contact rating: Contact service life:	3 A bei 240 V <sub>AC</sub> resistive load 350 000 operations at nominal load 900 000 operations at 1 A	
Controller type:	Limit comparators, limit controllers, pulse length controllers, pulse frequency controllers, modulating controllers, continuous controllers	<b>Optional board semi</b> Contact rating: Protective circuit:	i <b>conductor relay TRIAC</b> 1 A at 240 V <sub>AC</sub> Varistor	
Controller structure: P / PI / PD / PID		<b>Optional board 2 ser</b> Contact rating:	miconductor relay Photo-MOS $U \le 50 V_{AC/DC}$	
Optional boards To extend functionality 3 optional boards. Inputs (optional max. Optional board stand	,	Protective circuit: Optional board anale Measuring range: Load resistance: Accuracy:	I ≤ 200 mA ogue output 0(2) 10 V, 0 (4) 20 mA R <sub>load</sub> ≤ 500 Ω ≤ 0,5 %	
Measuring range:	0(2)10V, 01V	Interfaces / data logger (optional max. 1)		
Measuring accuracy:	(input resistence $R_E > 100 \text{ k}\Omega$ ) $O(4) \dots 20 \text{ mA}$ (Voltage drop $\leq 1.5 \text{ V}$ ) resistance sensor, min. 100 $\Omega$ , max. 4k $\Omega$ $\leq 0.05 \%$ (resistance ±4 $\Omega$ )	Optional board RS 4 Protocol: Baud rate: Device address: Max. number of participants:	<b>22/ 485</b> Modbus, Modbus Integer 9600, 19200, 38400 0255 32	
Ambient temperature effect: 100 ppm/K		Optional board Profibus DP Device address: 0255		
Power supply externa	al sensors (optional max. 3)	Optional board RS 485 with data logger		
Optional boards sup Output voltage:	<b>ply ISFET</b> ±5 V <sub>DC</sub> , 5 mA	The readout of data is only possible with the PC setup soft- ware! Further processing is possible with "Office" products.		
Optional boards sup		Data sets:	up to 43500 data sets	

Output voltage:

12 V<sub>DC</sub>, 10 mA

Data sets:	up to 43500 data sets
	(rings buffer)
Readout:	depending on the resolution
	10 hours up to 150 days

No responsibility taken for errors; subject to change without prior notice.



# Order Details (Example: APM-1 E 1 0 0 0 Y)

Model	Version	Housing	Power supply	<b>Option 1</b> (Optional board)	<b>Option 2</b> (Optional board)	<b>Option 3</b> (Optional board)	Special
APM Evaluation electronics pH/redox	1 = Compact-Line (new) Input: 1x pH/redox, 1x temperature/ standard signal, 2x binary input sensor supply: 2-wire transmitter, 2 relays	<ul> <li>E = for panel mounting</li> <li>F = Field housing</li> <li>S = Field housing with wall mounting bracket</li> <li>R = Field housing with pipe mounting bracket</li> </ul>	<b>1</b> = 110240 V <sub>AC</sub> -15%/+10%, 4863 Hz <b>2</b> = 2030 V <sub>AC/DC</sub> , 4863 Hz	<ul> <li>4 = analogue output 0(4)-20 mA, 0(2)-10 V (Standard)</li> <li>0 = without</li> <li>1 = universal input (resistance, current, voltage)</li> <li>2 = 1 relay (changeover contact)</li> <li>3 = 2 relays (NO with common pin)</li> <li>5 = 2 Photo-Mos relay switch (0.2 A)</li> <li>6 = 1 semiconductor relay TRIAC (1 A)</li> <li>7 = 1 power supply 4.85 V (e. g. for ISFET sensor)</li> <li>8 = 1 power supply 12 V<sub>oc</sub> (e. g. for inductive proximity switch)</li> </ul>	<ul> <li>0 = without</li> <li>1 = universal input (resistance, current, voltage)</li> <li>2 = 1 relay (changeover contact)</li> <li>4 = analogue output 0(4)-20 mA, 0(2)-10 V</li> <li>5 = 2 Photo-Mos relay switch (0.2 A)</li> <li>6 = 1 semiconductor relay TRIAC (1A)</li> <li>7 = 1 power supply 4.85 V (e. g. for ISFET sensor)</li> <li>8 = 1 power supply 12 V<sub>DC</sub> (e. g. for inductive proximity switch)</li> </ul>	$\begin{array}{l} 4.85 \ V \ (e. g. \ for \\ ISFET \ sensor) \\ \textbf{8} = 1 \ power \ supply \\ 12 \ V_{DC} \ (e. g. \ for \\ inductive \\ proximity \ switch) \\ \textbf{S} = Interface \end{array}$	0 = without (factory set) Y = adjusted according to customer specification


<sup>1)</sup> The readout of data is only possible with the PC setup software! Note: All languages are available in the device menu and can be changed by the customer at any time. The factory default setting of a language (except for "German") entail additional costs.

# Accessories for transmitter APM-1 and ACM-1

Version	Code
Setup-Software	ACM-Soft
PC-Interface with transducer USB/TTL with adapter (pins/connector)	ACM-Int
Mounting bracket for top hat rail, front size (96 x 48 mm)	ACM-Halt


# **Electrical connection**


(For details see manual or configuration sheet)







# Dimensions Panel Mounting









Panel cut-out



# Field Housing





1/07-2016